

LT8618EX--- Product Brief

Low Power HDMI Transmitter

Features

- HDMI 1.4 compliant transmitter with HDCP
- Support pixel rates above 340Mpix/second
- Support One Bit Audio (DSD, SACD)
- Low power consumption of 180mW at 1080P
- Less than 2mA standby power
- Pin compatible with Sil9030, ANX9030 and CAT6612
- Firmware programmable output swing and pre-emphasis
- Fully hardware-controlled or optional software-controlled HDCP operations
- Pre-programmed HDCP key sets or external EEPROM stored key sets
- Integrated CEC controller
- Integrated EDID shadow RAM and embedded EDID
- 5V-tolerant DDC interfaces
- Flexible video interface supports DVD and HD MPEG decoders
- 24-bit RGB/YCbCr 4:4:4
- 16/20/24-bit YCbCr 4:2:2
- 8/10/12-bit YCbCr 4:2:2 (ITU.601 and 656)
- 12-bit, dual-edge clocking input modes
- YCbCr-to-RGB color space conversion
- Input clock divider (0.5x, 2x, 4x)
- High-End digital audio interface
- 4 x I2S inputs accept Dolby Digital, DVD-Audio input

(2-ch. 192 kHz, 8-ch. 192 kHz)

- S/PDIF input supports PCM, Dolby Digital, DTS digital audio transmission (32-96 kHz Fs sample rate)
- IEC60958 or IEC61937 compatible
- Flexible, programmable I2S channel mapping
- Flexible, programmable I2S channel mapping
- 2:1 and 4:1 Down-sampling to handle 96 kHz and 192 kHz audio streams
- Fully integrated HDCP authentication hardware
- Master I2C interface for DDC connection simplifies board layout and lowers cost
- Flexible power management

Description

The LT8618EX is Lontium's low power version HDMI transmitter based on ClearEdge™ Technology. It supports the 24-bit color depth HDMI 1.4 (High Definition Multimedia Interface) specification. They are fully backward compatible with Lontium's first generation HDMI transmitter LT8618, and also pin compatible with Silicon Image Sil9030 and Analogix ANX9030 transmitters. LT8618EX is a high performance, low power part that are specifically designed for HD-Digital cameras, HD-Digital Video Cameras, HD-PMP/MP4 Players, Cell phones, etc. The normal operation power is less than 100mA playing 24bit 1080P content, and the standby power is less than 2mA.

Applications

- DVD, BD
- IPTV Box
- Car Video Recorder
- HD Sources



Figure 1. Application Diagram

Ordering Information

Part Number	Operating Temperature Range	Package	Packing Method
LT8618EXA	-40° C to +85° C	LQFP80 (12*12)	Tray

Part Number	Operating Temperature Range	Package	Packing Method
LT8618EXB	-40° C to +85° C	QFN64 (9*9)	Tape and Reel

Copyright © 2014、 2017 Lontium Semiconductor Corporation, All rights reserved.

Lontium Semiconductor Proprietary & Confidential

This document and the information it contains belong to Lontium Semiconductor. Any review, use, dissemination, distribution or copying of this document or its information outside the scope of a signed agreement with Lontium is strictly prohibited.

LONTIUM DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THOSE OF NONINFRINGEMENT, MERCHANTABILITY, TITLE AND FITNESS FOR A PARTICULAR PURPOSE. CUSTOMERS EXPRESSLY ASSUME THEIR OWN RISK IN RELYING ON THIS DOCUMENT.

LONTIUM PRODUCTS ARE NOT DESIGNED OR INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS WHERE A MALFUNCTION OF A LONTIUM DEVICE COULD RESULT IN A PERSONAL INJURY OR LOSS OF LIFE.

Lontium assumes no responsibility for any errors in this document, and makes no commitment to update the information contained herein. Lontium reserves the right to change or discontinue this document and the products it describes at any time, without notice. Other than as set forth in a separate, signed, written agreement, Lontium grants the user of this document no right, title or interest in the document, the information it contains or the intellectual property in embodies.

Trademarks

Lontium™ and ClearEdge™ is a registered trademark of Lontium Semiconductor. All Other brand names, product names, trademarks, and registered trademarks contained herein are the property of their respective owners.

Visit our corporate web page at: www.lontiumsemi.com

Technical support: support@lontium.com

Sales: sales@lontium.com